

Special Unit Bearing Replacement Motors

Bally



Stock No.	Watt Output	Volts	RPM	Amps	Rot. S.E.	Speeds	Capacitor	Motor Dia.	"A" Dim	Diameter & Length	Cross Reference	Notes
285	50W	230	1500	.85	CWLE	1	Shaded Pole	3-7/8"	3.50	5/16 x 1-1/2	ESPOL50EM2B	

Copeland



Stock No.	Watt Output	Volts	RPM	Amps	Rot. S.E.	Speeds	Capacitor	Motor Dia.	"A" Dim	Diameter & Length	Cross Reference	Notes
225	6W	115	1550	.36	CWLE	1	Shaded Pole	3-1/2"	2.78	1/4"-20 THD.	050-0241-0	
227	9W	115	1550	.58	CWLE	1	Shaded Pole	3-1/2"	2.78	1/4"-20 THD.	050-0241-0	
254	35W	115	1500	1.4	CWLE	1	Shaded Pole	3-7/8"	3.39	1/4"-20 THD.	050-0267-0	
258	50W	115	1500	1.7	CWLE	1	Shaded Pole	3-7/8"	3.50	3/8 x 1-1/2	050-0244-01	
260	50W	230	1500	.85	CWLE	1	Shaded Pole	3-7/8"	3.50	3/8 x 1-1/2	050-0244-00	
289	50W	115	1500	1.7	CWLE	1	Shaded Pole	3-7/8"	3.50	3/8 x 1-1/2	998-1008-00	
288	50W	230	1500	.85	CWLE	1	Shaded Pole	3-7/8"	3.50	3/8 x 1-1/2	050-0244-00	
276	50W	230	1500	.85	CCWLE	1	Shaded Pole	3-7/8"	3.75	5/16 x 2-1/2	050-0264-0	
290	50W	460	1500	.44	CWLE	1	Shaded Pole	3-7/8"	3.63	3/8 x 1.6	050-0244-02	

Crystal Tips



Stock No.	Watt Output	Volts	RPM	Amps	Rot. S.E.	Speeds	Capacitor	Motor Dia.	"A" Dim	Diameter & Length	Cross Reference	Notes
246	16W	115	1550	.80	CWLE	1	Shaded Pole	3-7/8"	3.39	1/4"-20 THD.	879-386857	

Gibson/Kelvinator



Stock No.	Watt Output	Volts	RPM	Amps	Rot. S.E.	Speeds	Capacitor	Motor Dia.	"A" Dim	Diameter & Length	Cross Reference	Notes
277	15W	115	1500	.60	CCW	1	Shaded Pole	3-7/8"	3-1/8	5/16 x 7-1/2	24-0366	

Hill Refrigeration



Stock No.	Watt Output	Volts	RPM	Amps	Rot. S.E.	Speeds	Capacitor	Motor Dia.	"A" Dim	Diameter & Length	Cross Reference	Notes
287	5W	115	1550	.45	CWLE	1	Shaded Pole	3-1/2"	2.50	1/4"-20 THD.	PP7577M	

Notes:
 *Rotation Determined by Viewing Lead End
 See Page 150 for Parts & Accessories