

J670 Series Utility Fan Kits



J620, J670, J672, J673, J675

- Kit includes one motor, two fans and mounting hardware
- Fan Diameters are 4", 5 1/2"
- Most popular series
- Individual motors also available
- Single and two speed models
- Physically reversible
- Used in commercial and residential freezer and refrigerator evaporators, vending machines, range hoods, exhaust fans, heaters and ventilators.

Vent Fan Kit



J575

- 50 CFM vent fan kit
- Universal bathroom replacement
- Physically reversible
- Kit includes one motor and one paddle fan.
- Fan Diameter 4 1/2"

Fireplace Fan



J574

- **Universal Fireplace Fan Replacement**
- **Mounting Brackets fit 4.12" B.C.D.**

Stock No. J670

Single Speed — CWSE
120 Volts, (5/8" stack), 3000 R.P.M., 60 Hz, .5 Amps
3/16 x 1 1/2 Dia. Shaft, Impedance protected
For motor only, use J370.
Cross Reference:
Gemline EM670, FASCO K670, Westward 33-670, WWG 4M987, MARS 90971, SUPCO SM670

Stock No. J672

Single Speed — CWSE
240 Volts, (5/8" stack), 3000 RPM, 60 Hz, .25 Amps,
3/16 x 1 1/2 Dia. Shaft, Impedance protected
For motor only, use J372.
Cross Reference:
Gemline EM672, FASCO K672, Westward 14005, Acme 602/702

Stock No. J673

Two Speed — CWSE
120 Volts, (5/8" stack), 3000/1550 RPM, 60 Hz, .5/1.3 Amps,
3/16 x 1 1/2 Dia. Shaft, Impedance protected
For motor only, use J373.
Cross Reference:
Gemline EM673, FASCO K673, Westward 33-673, WWG 4M075, Packard 65673, Acme AM-673

Stock No. J675

Single Speed — Reversible — Dual Voltage
120/240 Volts, (1 1/8" stack), 3000 RPM, 60 Hz, 1.1/1.55 Amps,
3/16 x 1 1/4 Dia. Breakaway Shaft, Thermally protected
Cross Reference:
Gemline EM675, Mars-90970, ACME Miami-7502, Westward 33-970, Supco SM-675, Packard 65675

Stock No. J620

Single Speed — CWSE — Ball Bearing
120 Volts, (5/8" stack), 3000 RPM, 60 Hz, .5 Amps
3/16 x 1 1/2 Dia. Shaft, Impedance protected
For motor only, use J320.
Cross Reference:
Acme BB-700, Same as J670 except ball bearing

Stock No. J575

Single Speed — CCWSE
120 Volts, (5/8" stack), 3000 RPM, 60 Hz, .65 Amps,
.181 x 1 1/2 Dia. Breakaway Shaft, Impedance protected
For motor only, use J375.
Cross Reference:
Maintenance Warehouse-250575

Stock No. J574 (discontinued) New # C10574

Single Speed — CCWSE — 100CFM
120 Volts, (1/2" stack), 2850 RPM, 60 Hz, .42 amps, Impedance protected
Cross Reference:
Rotom-RF100