



Dayton

3.3" Diameter Electric Motors Air Over Motor

	Model #	Mtg Pattern	Description	Shaft	Rotation Facing Shaft	Stud Location	Amps	60hz Volts
Open Air Over Motor								
	4M298	4	1/125HP, 3000RPM Reference: JA1C196	1/4"x7/8"	CCW	Flange	0.5	115
	3M534	1	1/100HP, 1550RPM	1/4"x2"	CW	SE	0.7	115
	3M535	1	1/100HP, 1550RPM	1/4"x2"	CCW	SE	0.7	115
	3M536	1	1/100HP, 1550RPM	1/4"x2"	CW	2BE	0.7	115
	4M192	1	1/100HP, 1550RPM	1/4"x2"	CCW	2/OSE	0.5	115
	3M537	1	1/100HP, 3000RPM	1/4"x2"	CW	2BE	.06	115
	3M538	1	1/70HP, 1550RPM Ref: JA1C195	1/4"x2 1/16"	CW	2/BE	0.7	115
	3M539	1	1/70HP, 1550RPM	1/4"x2 1/16"	CCW	2/BE	0.7	115

	3M540	1	1/70HP, 3000RPM	1/4"x2"	CW	SE	0.6	115
	3M541	1	1/70HP, 3000RPM	1/4"x2"	CW	OSE	0.6	115
	3M542	1	1/50HP, 1550RPM	1/4"x2"	CW	2/BE	0.9	115
	4M193	2	1/50HP, 1550RPM	1/4"x2"	CCW	OSE	0.8	115
	3M726	1	1/50HP, 1550RPM	5/16"X2"	CW	SE	0.5	230
	3M729	1	1/50HP, 3000RPM	1/4"x2"	CW	SE	1.0	115
	3M543	1	1/40HP, 1550RPM	5/16"X2"	CW	2/BE	1.1	115
	3M544	1	1/40HP, 1550RPM	5/16"X2"	CCW	2/BE	1.1	115
	3M722	1	1/40HP, 1550RPM	5/16"X2"	CW	SE	1.1	115
	3M724	1	1/40HP, 1550RPM	5/16"X2 1/16" Double Shaft	CW	2/BE	1.2	115
	3M545	1	1/40HP, 3000RPM	1/4"X2 1/16"	CW	2/BE	0.9	115

	3M728	1	1/40HP, 3000RPM	1/4"X2 1/16"	CW	SE	1.2	115
	3M730	1	1/40HP, 3000RPM	1/4"X2 1/16" Double Shaft	CCW	2/BE	1.0	115
	3M546	2	1/30HP, 1550RPM	5/16"X2"	CW	2/BE	1.1	115
	3M549	2	1/30HP, 1550RPM 2-Speed	5/16"X2 1/16"	CW	SE	1.2	115
	3M777	1	1/30HP, 3000RPM	5/16"X2 1/16"	CW	SE	1.2	115
	3M725	1	1/30HP, 3000RPM	5/16"X2 1/16"	CW	SE	0.6	230
	4M195	5	1/25HP, 1550RPM	1/4"x2" Double Shaft	CW	2/BE	1.8	115
	4M300	1	1/25HP, 3000RPM	1/4"x1"	CW	SE	1.9	115
	3M083	2	1/20HP, 1550RPM	1/4"X2 1/16" Double Shaft	CCW	4/BE	1.8	115
	3M547	2	1/20HP, 1550RPM	5/16"X2"	CW	2/BE	1.8	115
	3M778	2	1/20HP, 1550RPM Old # 8M209	5/16"X2"	CW	SE	1.8	115

	4M301	3	1/15HP, 1550RPM	5/16"X1 3/4"	CCW	3-LUG	2.7	115
	3M548	2	1/15HP, 3000RPM	5/16"X2"	CW	SE	2.2	115
Shaded Pole Motor - Open Air Over Motor								
	3M558	1	1/100HP, 1550RPM	1/4"X2 1/16"	CW	2/BE	0.7	115
	3M560	1	1/70HP, 1550RPM	1/4"x2"	CW	2/BE	0.7	115
	3M561	1	1/70HP, 1550RPM	1/4"x1.5"	CCW	4/SE	0.7	115
	3M562	1	1/40HP, 1550RPM	5/16"X2"	CW	2/BE	1.0	115
	3M563	1	1/40HP, 1550RPM	5/16"X2"	CCW	2/BE	1.0	115
	2PUX4	<p>Old # 3M564 (Fasco) 2PUX4 Dayton brand-made in China Vibrator Motor Shaded Pole, Open Enclosure 1/200 HP, 1550 Nameplate RPM Full Load Amps 0.5, 115V, 60 Hz.</p>						115
	D1130	<p>Fasco Brand Vibrator Motor This is the original motor made for Dayton-made in Mexico 1/200HP, 1550RPM, .5 amps Open Ventilated</p>						115
	10C904	<p>Mounting Bracket for Vibrator Motor Includes Bolt and Nut to Secure Base to Motor Old # 2C703, 2PUX5</p>						