





# **ECM Fan Coil Replacement Motor**

(Electronically Commutated Motor)



#### **Features**

- Drop-in replacement
- Single phase
- Brushless DC
- 3 speeds
- 5 1/8" diameter
- 54" lead length
- Energy efficient

# A. O. Smith's new Comfort Select~FC is a brushless DC high efficiency motor that runs off 120 volt single phase input. The motor is controlled by integrated electronics providing advanced motor protection with the same performance characteristics as a shaded pole or PSC (permanent split capacitor) motor. The Comfort Select~FC is designed as a direct replacement or retrofit product for shaded pole and PSC motors and may be used in fan coil and PTAC\* applications as an energy saving retrofit.



### **Benefits**

- ECM with internal control
- Long life ball bearings
- Rotors are isolated from shaft to reduce motor vibration
- Saves an average of 69% on energy usage
- Runs cooler
- Easy to install

# **Applications**

Fan Coils, Air Conditioners, Blowers, Shaded Pole, PSC Retrofit, Trane, Carrier, Amana, GE, Fan Coil & PTAC Units

## **Specifications**

Stock Number	HP	Speeds	RPM	Volts	Amps	Frame	Rotation	Shaft Dia. & Length
CS89	1/10	3	1100,900,700	120	1.56	42	CWLE	9.3 x 1/2"x 9.3

\*Packaged Terminal Air Conditioner





#### **Energy Saving Comparison**





kWh= KiloWatt hours

#### **Average Annual Savings:**

69% \$106.40

l	<b>Total Building Savings</b>	Single Unit Savings	(X)	Number of Units	(=)
	CS89 Replacing Shaded Pole	\$106.40		J 95	\$10,108.46





Divisional Headquarters
A. O. Smith Electrical Products Company
531 North Fourth Street
Tipp City, OH 45371
A DIVISION OF A. O. SMITH CORPORATION

ROHS



**NOW AVAILABLE!**FAX OR PHONE YOUR ORDER TODAY!

Distribution Services 1325 Heil Quaker Blvd. LaVergne, TN 37086 (800) 672-6495 Fax: (800) 468-2062 www.hvac-motors.com

Bulletin #6855A 4/11

Copyright © 2011 A. O. Smith Corporation